

**FENDER BROWNFACE (BROWN OR BLONDE TOLEX, 1960-1963) POT REPLACEMENT CHART PAGE 1 OF 2**

POT PART #	POT DESCRIPTION	BANDMSTR 6G7	BANDMSTR 6G7A	BASSMAN 6G6	BASSMAN 6G6A	BASSMAN 6G6B	CONCERT 6G12	CONCERT 6G12A	DELUXE 6G3	PRINCETON 6G2	PRO-AMP 6G5	PRO-AMP 6G5A
P-FBF-5KL	5KB LIN 24MM	P					P					
P-FBF-25KL	25KL LIN 24MM		P	P, B1	P, B1	P, B1		P				P
P-FBF-50KRA	50KC REV AUD 24MM											
P-FBF-100KL	100KB LIN 24MM	I		T1	T1							
P-FBF-250KA	250KA AUD 24MM	B1, B2	B1, B2	V1, B2	B2	T1, B2	B1, B2	B1, B2			B1, B2	B1, B2
P-FBF-250KL	250KB LIN 24MM	T1, T2			V1	V1	T1, T2	T1, T2	I	I	T1, T2	
P-FBF-350KA/T70K	350KA AUD/70K TAP		T1, T2	T2	T2	T2						T1, T2
P-FBF-500KL	500KB LIN 24MM	V1, V2					V1, V2				V1, V2	
P-FBF-1MA	1MA AUD 24MM		V1, V2	V2	V2	V2		V1, V2	V1, V2, TN1, TN2	V1, TN1		V1, V2
P-FBF-3MRA	3MC REV AUD 24MM	S	S				S	S	S	S	S	S
P-FBF-10MRA	10MC REV AUD 24MM		I				I	I			I	I

ABBREVIATIONS KEY	
V1	VOLUME - CHAN 1
V2	VOLUME - CHAN 2
B1	BASS - CHAN 1
B2	BASS - CHAN 2
T1	TREBLE - CHAN 1
T2	TREBLE - CHAN 2
I	INTENSITY
S	SPEED
P	PRESENCE
R	REVERB

Studio Sound Electronics    [amprepairparts . Com](http://amprepairparts.com)

**FENDER BROWNFACE (BROWN OR BLONDE TOLEX, 1960-1963 POT REPLACEMENT CHART PAGE 2 OF 2**

POT PART NUMBER	POT DESCRIPTION	SHOWMAN 6G14	SHOWMAN 6G14A	SUPER-AMP 6G4	SUPER-AMP 6G4A	TREMOLUX 6G9	TREMOLUX 6G9A	TREMOLUX 6G9B	TWIN-AMP 6G8	TWIN-AMP 6G8A	VIBRASONIC 6G13A	VIBROLUX 6G11
P-FBF-5KL	5KB LIN 24MM	P		P					P			
P-FBF-25KL	25KL LIN 24MM		P		P					P	P	
P-FBF-50KRA	50KC REV AUD 24MM											
P-FBF-100KL	100KB LIN 24MM											
P-FBF-250KA	250KA AUD 24MM		B1, B2	B1, B2	B1, B2	I, B1, B2	I, B1, B2	I, B1, B2		B1, B2	B1, B2	I, B1, B2
P-FBF-250KL	250KB LIN 24MM			T1, T2								
P-FBF-350KA/T70K	350KA AUD/70K TAP	T1, T2	T1, T2		T1, T2	T1, T2	T1, T2	T1, T2	T1, T2	T1, T2	T1, T2	T1, T2
P-FBF-500KL	500KB LIN 24MM	V1, V2		V1, V2					V1, V2			
P-FBF-1MA	1MA AUD 24MM	B1, B2	V1, V2		V1, V2	V1, V2	V1, V2	V1, V2	B1, B2	V1, V2	V1, V2	V1, V2
P-FBF-3MRA	3MC REV AUD 24MM	S	S	S	S	S	S	S	S	S	S	S
P-FBF-10MRA	10MC REV AUD 24MM	I	I	I	I				I	I	I	

**ABBREVIATIONS KEY**

V1	VOLUME - CHAN 1
V2	VOLUME - CHAN 2
B1	BASS - CHAN 1
B2	BASS - CHAN 2
T1	TREBLE - CHAN 1
T2	TREBLE - CHAN 2
I	INTENSITY
S	SPEED
P	PRESENCE
R	REVERB